

Arcadia R4.0 & R4.1 Keypanel Capabilities



	Arcadia Essential Features	Eclipse Features
Keypanels		
V-Series 12 Key	Yes	Yes
V-Series 24 Key	Yes	Yes
V-Series 32 Key	Yes	Yes
V-Series 12 Key Desktop	Yes	Yes
V-Series Expansion Panels	No	Yes
2X10 Touch 20 Key Desktop	No	Yes
Connectivity		
I.V. Connectivity	Yes	Yes
AES67 Network	Yes,**	Yes*
Analog 4-Wire	No	Yes
Roles		
Roles	Yes	Yes
Role Teams, Access & USB	No	Yes
Key		
Types	Channel, Group, IFB,** Role, Interface	Channel, Group, IFB, Role, Interface, Sort Group, Dynam-EC Key Group, Control, Telephone
Assignment	Combined Talk & Listen	Separate Talk & Listen*
Secondary Talk Action	Call, per Key**	Control, per System setting
In-Use Tally	Yes, per Key**	Yes, per System setting
Level Control	Crosspoint	Crosspoint, Input, Output
Interlock Group	1**	9
Key Stacking	No	Yes
Shift Pages	No	9
Audio I/O & Panel Mixer		
Headset, Gooseneck & Speaker	Yes	Yes
Secondary Headset	No	Yes
Mic Input EQ & Dynamics	Fixed	Adjustable
External Inputs & Outputs	Fixed Routing to Headset	Configurable Routing with IFB
Main & Hot Mic Output	Yes	Yes
Hosted Direct	No	Yes, up to 2
Logic Inputs & Outputs		
Logic Input (GPI) 1-4	Role Configurable to: Mic (toggle, momentary), Talk, Mute Panel to System, Reply Key, Pre-Selected Talk Keys, Speaker Mute, Listen Again GPI 1 assignable to Logic action	1 & 2: Configurable to: Mic (toggle, momentary), Talk, Mute to System, Reply Key, Reply Key & Clear, Configured Action (Talk/Listen to any port, Channel, Group, IFB, Control), Pre-Selected Talk Keys, Pre-Selected PTT Keys 3: Fixed to: Reply 4: Fixed to: Supervisor Mode Exit
Logic Output (GPO/Relay) 1 & 2	Yes, GPO 1 assignable to Logic trigger	Yes, Controls
Assignments - From Panel		
Partyline	No	Yes
Fixed Group	No	Yes
IFB	No	Yes
Administration		
Menu with Access Control	Yes	Yes
System Configuration, Key Assignment, & Diagnostics	No	Yes
Supervisor Mode	No	Yes
General		
Listen Again	Yes	Yes
Messaging	No	Yes

Notes:
* Keypanel type dependent
** Arcadia release 4.1