Arcadia R4.0 & R4.1 Keypanel Capabilities





	Arcadia Essential Features	Eclipse Features
Keypanels		
	Voc	Vec
V-Series* 12 Key	Yes	Yes
V-Series* 24 Key	Yes Yes	Yes
V-Series* 32 Key		Yes
V-Series* 12 Key Desktop	Yes. Limited Support with 1RU Role Type*	Yes Yes
V-Series Expansion Panels	No No	Yes
2X10 Touch 20 Key Desktop	No	res
Connectivity		
I.V. Connectivity	Yes	Yes
AES67 Network	Yes***	Yes***
Analog 4-Wire	No	Yes
Roles		
Roles	Yes	Yes
Role Teams, Access & USB	No	Yes
Note Teams, 7 (eeess & OSB	140	163
Key		
Types	Channel, Group, IFB**, Role, Interface	Channel, Group, IFB, Role, Interface, Sort Group, Dynam-EC Key Group, Control, Telephone
Assignment	Combined Talk & Listen	Separate Talk & Listen***
Secondary Talk Action	Yes, using Logic configuration	Control, per port setting
In-Use Tally	Yes; Role, Channels, Groups, IFB**, Interface Outputs	Yes, per System settings
Level Control	Crosspoint	Crosspoint, Input, Output
Interlock Group	No	9
Key Stacking	No	Yes
Shift Pages	No	9
Audio I/O & Panel Mixer		
Headset, Gooseneck & Speaker	Yes	Yes, configurable
Secondary Headset	Fixed Level Listen	Yes, configurable
Mic Input EQ & Dynamics	Fixed	Yes, configurable
External Inputs & Outputs	External Inputs Routed to Headset with Aux Level Control	Configurable Routing with IFB Controls
Main & Hot Mic Output	Main with Main Level Control. Hot Mic Fixed Level.	Yes, configurable
Hosted Direct	No	Yes, up to 2
	1.0	100, 45 00 2
Logic Inputs & Outputs Logic Input (GPI) 1-4 Note: -X7 PTT is paralleled with 1 & 2	Role Configurable to: Mic (toggle, momentary), Talk, Mute Panel to System, Reply Key, Pre-Selected Talk Keys, Speaker Mute, Listen Again GPI 1 assignable to Logic action	1 & 2: Configurable to: Mic (toggle, momentary), Talk, Mute to System, Reply Key, Reply Key & Clear, Configured Action (Talk/Listen to any port, Channel, Group, IFB, Control), Pre-Selected Talk Keys, Pre-Selected PTT Keys 3: Fixed to: Reply 4: Fixed to: Supervisor Mode Exit
Logic Output (GPO/Relay) 1 & 2	GPO 1 ("Aux") assignable to Logic trigger	Yes, Controls
Assignments - From Panel		
Partyline	No	Yes
Fixed Group	No	Yes
IFB	No	Yes
Administration		
Menu with Access Control	Yes	Yes
System Configuration, Key	No Yes	Yes
Assignment, & Diagnostics	140	। ਵੱਠ
Supervisor Mode	No	Yes
General		
Listen Again	Yes	Yes
Messaging	No	Yes

Notes:



^{*}V-Series Iris and IrisX keypanels support all Arcadia features. Non-Iris panels are partially supported in Arcadia with I.V. port connectivity only, cannot be upgraded from the Arcadia and must use 1RU role type for desktop

^{**}Arcadia release 4.1

^{***}Keypanel type dependent.