

FreeSpeak Family Beltpack Options



FreeSpeak Cell

- Frequency**
5G/LTE Cellular
- System Options**
Eclipse HX via E-IPA Card
- Dual SIM Operation**
Switch between Private and Public cellular
- Beltpacks Per System**
400+
- Controls**
8 Push Buttons
1 Reply Key
4 Level Controls
1 Main Level Control
- Battery Life**
8+ Hours (Li-Ion)
- Bluetooth® Connectivity**
Yes



FreeSpeak Edge

- Frequency**
5 GHz
- System Options**
Arcadia Central Station
FreeSpeak Edge Base Station
Eclipse HX via E-IPA Card
- Beltpacks Per System**
Arcadia: 64
FS Edge: 16
E-IPA Card: 255
- Transceivers**
IP TCVR (5.0 GHz)
- Beltpacks Per Transceiver**
IP TCVR (5.0 GHz): 10 BPs
- Controls**
8 Push Buttons
1 Reply Key
4 Level Controls
1 Main Level Control
- Battery Life**
12+ Hours (Li-Ion)
- Bluetooth® Connectivity**
No



FreeSpeak Icon

- Frequency**
1.9 GHz
- System Options**
Arcadia Central Station
FreeSpeak Edge Base Station
Eclipse HX via E-IPA Card
- Beltpacks Per System**
Arcadia: 64
FS Edge: 16
E-IPA Card: 255
- Transceivers**
IPT (1.9 GHz)
E1 (1.9 GHz)
- Beltpacks Per Transceiver**
IPT (1.9 GHz): 10 BPs
E1 (1.9 GHz): 5 BPs
- Controls**
8 Push Buttons
1 Reply Key
4 Level Controls
1 Main Level Control
- Battery Life**
18+ Hours (Li-Ion)
- Bluetooth® Connectivity**
Yes



FreeSpeak II 2.4

- Frequency**
2.4 GHz
- System Options**
Arcadia Central Station
FreeSpeak Edge Base Station
FreeSpeak II Base-II Base Station
FreeSpeak II 5-up Base Station
Eclipse HX via E-IPA Card
- Beltpacks Per System**
Arcadia: 64 FS Edge: 25
FS II: 25 FS II 5-Up: 5
E-IPA Card: 160
- Transceivers**
E1 (2.4 GHz)
- Beltpacks Per Transceiver**
E1 (2.4 GHz): 4 BPs
- Controls**
4 Push Buttons
1 Reply Key
2 Level Controls
- Battery Life**
18+ Hours (Li-Ion)
9 Hours (AA)
- Bluetooth® Connectivity**
No



FreeSpeak II 1.9

- Frequency**
1.9 GHz
- System Options**
Arcadia Central Station
FreeSpeak Edge Base Station
FreeSpeak II Base-II Base Station
FreeSpeak 5-Up Base Station
Eclipse HX via E-IPA Card
- Beltpacks Per System**
Arcadia: 64 FS Edge: 25
FS II: 25 FS II 5-Up: 5
E-IPA Card: 255
- Transceivers**
IPT (1.9 GHz)
E1 (1.9 GHz)
- Beltpacks Per Transceiver**
IPT (1.9 GHz): 10 BPs
E1 (1.9 GHz): 5 BPs
- Controls**
4 Push Buttons
1 Reply Key
2 Level Controls
- Battery Life**
18+ Hours (Li-Ion)
9+ Hours (AA)
- Bluetooth® Connectivity**
Yes